



NWAA Labs Inc
25132 Rye Canyon Loop, Santa Clarita, CA 91355
253-973-1018 or 253-229-7448

Speaker # _____
Model # **C10.1R Baff**
SN# _____

Customer

Name Martin Audio Ltd
Address Century Point, Halifax Rd, Cressex Buisness Park

City High Wycombe State Buckingham ZIP HP123SL
Phone 011-44-1494535312

Misc

Form Date 10/11/2006
Test date 10/11/2006

Ret Date _____
Status _____

SENSITIVITY WORKSHEET - 1/3 OCT.

| | |
|---------------------|--------------|
| Speaker Voltage | 5.07V 16 ohm |
| Measuremt Distance: | 4.01 meters |

| <u>Frequency</u> | <u>Measured</u> | <u>Corrected</u> |
|------------------|-----------------|------------------|
| 100 Hz | | 92.3 |
| 125 Hz | | 92.1 |
| 160 Hz | | 90.3 |
| 200 Hz | | 90.1 |
| 250 Hz | | 90.0 |
| 315 Hz | | 89.0 |
| 400 Hz | | 89.3 |
| 500 Hz | | 88.8 |
| 630 Hz | | 88.1 |
| 800 Hz | | 87.9 |
| 1000 Hz | | 89.2 |
| 1250 Hz | | 90.0 |
| 1600 Hz | | 90.8 |
| 2000 Hz | | 90.0 |
| 2500 Hz | | 90.0 |
| 3150 Hz | | 89.9 |
| 4000 Hz | | 91.4 |
| 5000 Hz | | 91.7 |
| 6300 Hz | | 91.9 |
| 8000 Hz | | 93.0 |
| 10000 Hz | | 93.2 |